2/5/04

EH 1435

Document And Report Documentation Page Submitted as edoc_1075730062

Report Documentation Page			*Form Approved* *OMB No. 0704-0188*
Public reporting burden for the collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington VA 22202-4302. Respondents should be aware that notwithstanding any other provision of law, no person shall be subject to a penalty for failing to comply with a collection of information if it does not display a currently valid OMB control number.			
1. REPORT DATE **13 MAR 2003**	2. REPORT TYPE **N/A**	3. DATES COVERED -	
4. TITLE AND SUBTITLE **Matched Subspace Detectors for Stochastic Signals**			5a. CONTRACT NUMBER
			5b. GRANT NUMBER
			5c. PROGRAM ELEMENT NUMBER
6. AUTHOR(S)			5d. PROJECT NUMBER
			5e. TASK NUMBER
			5f. WORK UNIT NUMBER
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) **Mission Research Corporation and Colorado State University**			8. PERFORMING ORGANIZATION REPORT NUMBER
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES)			10. SPONSOR/MONITOR'S ACRONYM(S)
			11. SPONSOR/MONITOR'S REPORT NUMBER(S)
12. DISTRIBUTION/AVAILABILITY STATEMENT **Approved for public release, distribution unlimited**			
13. SUPPLEMENTARY NOTES **Also see: ADM001520, The original document contains color images.**			
14. ABSTRACT			
15. SUBJECT TERMS			
16. SECURITY CLASSIFICATION OF:	17.	18.	19a. NAME OF RESPONSIBLE

a. REPORT	b. ABSTRACT	c. THIS PAGE	LIMITATION OF ABSTRACT	NUMBER OF PAGES	PERSON
unclassified	**unclassified**	**unclassified**	**UU**	**17**	**Patricia Mawby, EM 1438** **PHONE:(703) 767-9038** **EMAIL:pmawby@dtic.mil**

Standard Form 298 (Rev. 8-98)
Prescribed by ANSI Std Z39-18

pwd: cannot determine current directory!

Matched Subspace Detectors for Stochastic Signals*

Todd McWhorter

Mission Research Corporation

mcwhorter@aster.com

Louis Scharf

Colorado State University

scharf@engr.colostate.edu

*This work supported by ONR contracts N00014-00-C-00145 and N00014-01-1-1019-P0001

Mission Research Corporation

Colorado State University

Knowledge to Go Places

Matched Subspace Detectors for Stochastic Signals*

Todd McWhorter

Mission Research Corporation

mcwhorter@aster.com

Louis Scharf

Colorado State University

scharf@engr.colostate.edu

*This work supported by ONR contracts N00014-00-C-00145 and N00014-01-1-1019-P0001

Problem Statement

- The goal is to design detectors for stochastic signals or second-order signals.
- Extension of the first-order matched subspace detectors of Scharf and Friedlander.
- It is assumed that interference is nulled prior to processing by projecting the data into the space orthogonal to the interference subspace.
- We assume various states of knowledge about the parameters σ^2 and β.

θ



$$n \sim CN(0, \sigma^2 I)$$

$$\theta : f(\theta;\beta) \quad \text{ex. } \theta \sim CN(0, R_{\theta\theta})$$

Pre-Processing

- In order to be invariant to the interference statistics, the data are projected into the space orthogonal to the interference.
- The data are then decomposed into their signal and noise components.
- The signal component is denoted by the vector z and the noise component is denoted by the vector w.



$G = (I-P_S)H$

$$z = (H^*(I-P_S)H)^{-1/2}H^*(I-P_S)\,y = (G^*G)^{-1/2}G^*\,y$$

$AA^* = I - P_S - P_G \qquad w = A^*\,y$

Hypotheses

- The "noise" vector w is distributed as a white complex Gaussian vector regardless of which hypothesis is in effect.

$$f(\mathbf{w}) = \frac{1}{(\pi\sigma^2)^{N-p}} e^{-\frac{\mathbf{w}^*\mathbf{w}}{\sigma^2}}$$

- Define $\phi = (G^*G)^{1/2}\theta$.

- When signal is present the data vector z is distributed:

$$f(\mathbf{z} \mid \phi) = \frac{1}{(\pi\sigma^2)^p} e^{-\frac{1}{\sigma^2}\|\mathbf{z}-\phi\|^2}$$

- When signal is not present the data vector z is distributed:

$$f(\mathbf{z} \mid \phi = 0) = \frac{1}{(\pi\sigma^2)^p} e^{-\frac{\mathbf{z}^*\mathbf{z}}{\sigma^2}}$$

Likelihood Ratio

- For now, assume that the noise power σ^2 is known.

- In this case the vector w is common to both hypotheses and is of no use.

- The *conditional* likelihood ratio is then

$$l(\mathbf{z} \mid \phi; \sigma^2) = \frac{f(\mathbf{z}|\phi;\sigma^2)}{f(\mathbf{z}|\phi=0;\sigma^2)}$$

$$= \exp\left(\frac{\mathbf{z}^*\mathbf{z}}{\sigma^2}\right) \times \exp\left(-\frac{1}{\sigma^2}\|\mathbf{z}-\phi\|^2\right)$$

Unconditional Likelihood Ratio

- **The unconditional likelihood ratio can be written as**

$$l(\mathbf{z};\sigma^2,\beta) = \exp\left(\frac{\mathbf{z}^*\mathbf{z}}{\sigma^2}\right) \times \int \exp\left(-\frac{\|\mathbf{z}-\phi\|^2}{\sigma^2}\right) f_\phi(\phi;\beta)\,d\phi$$

- **The log-likelihood ratio becomes**

$$s(\mathbf{z};\sigma^2,\beta) = \frac{\mathbf{z}^*\mathbf{z}}{\sigma^2} + \ln \int \exp\left(-\frac{\|\mathbf{z}-\phi\|^2}{\sigma^2}\right) f_\phi(\phi;\beta)\,d\phi$$

$$= \underbrace{\frac{\mathbf{y}^*\mathbf{P_G}\mathbf{y}}{\sigma^2}}_{\text{Matched Subspace Detector}} - \underbrace{p_r(\mathbf{z};\sigma,\beta)}_{\text{Resolution penalty}}$$

Matched Subspace Detector

Resolution penalty

Resolution Penalty

- The resolution penalty occurs because we presume to know something about the coordinate vector θ .
- If z is far from the "favored" orientation defined by θ then the penalty is larger than if the converse were true.

$$p_r(\mathbf{z}; \sigma^2; \beta) = -\ln \int \exp\left(-\frac{\|\mathbf{z}-\phi\|^2}{\sigma^2}\right) f_\phi(\phi; \beta)\, d\phi$$

Gaussian Coordinate Vectors

- **Suppose $\phi \sim CN(0,R_{\phi\phi})$.**
- **Write the eigenvalue decomposition of $R_{\phi\phi}$ as:**

$$R_{\phi\phi} = (G^*G)^{1/2} R_{\theta\theta} (G^*G)^{1/2} = V D^2 V^*$$

$$V = [\mathrm{v}_1 \, \mathrm{v}_2 \cdots \mathrm{v}_p]; \quad \textit{unitary}$$

$$D^2 = diag[\beta_1^2, \beta_2^2, \cdots, \beta_p^2]$$

- **Define the resolved signal-plus-noise to noise ratios:**

$$r_i = 1 + \frac{\beta_i^2}{\sigma^2}$$

Gaussian Penalty Term

- **After some algebra the penalty term can now be written as**

$$p_r(\mathbf{z}; \sigma^2, \beta^2) = -\ln \int \exp\left(-\frac{\|\mathbf{z}-\phi\|^2}{\sigma^2}\right) \frac{1}{\pi^p det(R_{\phi\phi})} \exp(-\phi^* R_{\phi\phi}^{-1} \phi) d\phi$$

$$= \sum_{i=1}^{p} \ln(r_i) + \sum_{i=1}^{p} \frac{(\mathbf{z}^* P_{\mathbf{v}_i} \mathbf{z}/\sigma^2)}{r_i}$$

- **This result implies that if the estimated signal-plus-noise to noise ratio ($\mathbf{z}^* P_{v(i)}\, \mathbf{z} / \sigma^2$) in the resolved subspace defined by $\mathbf{v}_i$ greatly exceeds r_i, then the penalty is large because of this mismatch.**

Unknown Signal Power and Orientation

- Suppose that when signal is present we do not know $R_{\phi\phi}$.

- Recall the penalty term is

$$p_r(\mathbf{z};\sigma^2,\beta^2) = -\ln \int \exp\left(-\frac{\|\mathbf{z}-\phi\|^2}{\sigma^2}\right)\frac{1}{\pi^p det(R_{\phi\phi})}\exp(-\phi^* R_{\phi\phi}^{-1}\phi)d\phi$$

$$\mp \sum_{i=1}^{p} \ln(r_i) + \sum_{i=1}^{p} \frac{\left(\mathbf{z}^* P_{\mathrm{V}_i}\mathbf{z}/\sigma^2\right)}{r_i}$$

- The estimates of the signal-plus-noise to noise ratios are

$$r_i = max(1, \mathbf{z}^* P_{\mathrm{V}_i}\mathbf{z}/\sigma^2)$$

- We assume that $r_i \geq 1$ in the sequel.

Estimating Orientation

- The estimates of r_i in the previous slide depend on the orientation of the vectors v_i .

- We want to minimize

$$\prod_{i=1}^{p} \frac{\mathbf{z}^* P_{\mathbf{v}_i} \mathbf{z}}{\sigma^2}$$

- We must also satisfy the constraints

$$\sum_{i=1}^{p} \frac{\mathbf{z}^* P_{\mathbf{v}_i} \mathbf{z}}{\sigma^2} = \frac{\mathbf{z}^* \mathbf{z}}{\sigma^2} \qquad r_i = \frac{\mathbf{z}^* P_{\mathbf{v}_i} \mathbf{z}}{\sigma^2} \geq 1$$

Intermediate Orientation Solution

- The solution to this optimization problem is

$$r_i = \frac{\mathbf{z}^* P_{\mathbf{v}_i} \mathbf{z}}{\sigma^2} = 1 \quad for \ i = 1, 2, \cdots, p-1$$

$$r_p = \frac{\mathbf{z}^* P_{\mathbf{v}_p} \mathbf{z}}{\sigma^2} = \frac{\mathbf{z}^* \mathbf{z}}{\sigma^2} - (p-1)$$

- The question remains: Is there a decomposition of $\langle$ G $\rangle$ that has the above properties?

- The answer is yes.

Orientation Solution

- Solve for v_p first.
- Choose a v_p on the spherical invariance set defined by

$$\frac{z^* P_{v_p} z}{\sigma^2} = \frac{z^* z}{\sigma^2} - (p-1).$$

- Repeat this procedure in the spaces $\langle A_{p-1} \rangle, \langle A_{p-2} \rangle,$ 6 $, \langle A_1 \rangle$



Compressed Likelihood

- Compressing the likelihood ratio with this solution gives the statistic

$$s(\mathbf{z};\sigma^2,\hat{R}_{\phi\phi}) = \frac{\mathbf{y}^* P_H \mathbf{y}}{\sigma^2} - \left[\ln\left(\frac{\mathbf{y}^* P_H \mathbf{y}}{\sigma^2}\right) - constants\right]$$

- This statistic is a monotonic function of the matched subspace detector. We can therefore use the MSD as the detection statistic

$$s = \frac{\mathbf{y}^* P_H \mathbf{y}}{\sigma^2}$$

- Then the result for 2nd-order models is the same as for 1st-order models.

Unknown Noise Power

- In the case of unknown noise power the GLRT detector can be written as a sum of the CFAR matched subspace detector and a penalty term

$$s(\mathbf{z};\hat{\sigma}^2,\hat{R}_{\phi\phi}) = \ln(1+\tilde{s}) - [\ln(\tilde{s}) - constants]$$

- We can equivalently use the statistic

$$\tilde{s} = \frac{\mathbf{y}^* P_H \mathbf{y}}{\hat{\sigma}^2}; \qquad \hat{\sigma}^2 = \frac{1}{N-p}\mathbf{y}^*(I - P_H)\mathbf{y}$$

- These detectors are identical to the 1st-order results.

Rank-One Assumptions

- Here we assume that the signal subspace is rank-one.
- The complex-valued signal amplitude is written in polar form

$$\theta = Me^{j\phi}$$

- Assume that the phase and magnitude are uncorrelated and that the phase is uniformly distributed over $[0, 2\pi)$.
- Assume that the signal magnitude has a generalized Rayleigh distribution

$$f_M(M) = \frac{2M}{\beta^2}\left(\frac{M^2}{\beta^2}\right)^L \frac{e^{-M^2/\beta^2}}{L!}$$

Detectors with Known Noise

- L=0. This is the previous results with complex Gaussian amplitudes.

- $L \neq 0$. The penalty function is

$$p_r = (L+1)\ln(r) + \frac{(\mathrm{y}^* P_h \mathrm{y}/\sigma^2)}{r} - \ln\left[\sum_{k=0}^{L} \frac{binom(L,k)}{k!} \left(\frac{(\mathrm{y}^* P_h \mathrm{y}/\sigma^2)(r-1)}{r}\right)^k\right]$$

- Minimize the penalty term with respect to $r=1+\beta^2/\sigma^2$.
- Compress the likelihood function with this term to obtain

$$s = \frac{\mathrm{y}^* P_h \mathrm{y}}{\sigma^2} - p_r(\widehat{r}).$$

Mission Research Corporation

Colorado State University
Knowledge to Go Places